

At 1500rpm Prime Power 1204KWe/1505KVA, Standby Power 1325KWe/1656KVA

At 1800rpm Prime Power 1208KWe/1510KVA, Standby Power 605KWe/1669KVA

Features

Engine	Perkins
Type	4012-46TAG2A
Origin	UK
No. of Cylinders	12
Configuration	V
SAE/Flexible coupling	0/18"
Cycle	4-stroke
Bore, mm	160
Stroke, mm	190
Displacement, l	45.84
Compression ratio	13.6:1
Aspiration	Turbocharged
Injection	Electronic
Starting	24VElectric
Alternator, amps	80/24V

Alternator	Stamford
Type	PI734C
Origin	UK
Construction	single bearing
Insulation system	Class"H"
Temperature rise, °C	125
Excitation	PMG
Voltage Regulator	AVR MX341
Protection	IP 23
Rated power factor	0.8
Regulation	±1.0%
No. of Phases	3
No. of Poles	4
RPM	1500 1800
Frequency	50Hz 60Hz

Performances	1500rpm	1800rpm
Engine		
Efficiency		94%
Prime Power, KWm (hp)	1267(1700)	1272 (1706)
Standby Power, KWm (hp)	1395(1870)	1399 (1876)

Fuel system	1500pm	1800pm
Specific fuel consumption at:		
Prime Power, Litre/h		
50%	162	171
75%	237	195
100%	301	319

GENERATING SET POWERED BY PERKINS

SP1650- GENSET

Circuit Breaker

3Pole series ACB , amps	2500
CT's	2500/5
Steel sheet enclosure with bolted cover (European origin, ABB or equivalent)	

Documentation

Engine instruction book-English
Warranty and service book- Multi-language
Alternator manual- English
Wiring diagram

Dimensions and Weight

Length: 5.00m
Width: 2.25m
Height: 2.65m
Weight: 9785Kg

Spare Parts Kit (Optional)

(Genuine Perkins)

Oil filter, full flow	2
Oil filter, bypass	1
Fuel filter	1
Fuel filter water separator	1
Coolant filter	1
Air filter	2
Fan belt set	1
Alternator belt set	1

International Standards

Engine conform to ISO 9001: 2000, ISO 14001, ISO10054, ISO 3046, BS 5514, DIN 6271.
Alternator conform to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861-1, B En 61000-6-2:2001.

Rating Guidelines

PRIME POWER rating to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load with 70% load factor for an unlimited number of hours as opposed to commercially purchased power. A 10% overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating.

1 hp = 1KW x 1.36

KWm = Kilo Watt mechanical, net with fan

KWe = Kilo Watt electrical = KWm*gen.eff

KVA = Kilo Volt Ampere calculations based based on 0.8 power factor = KWe/0.8

Optional Equipment

• Engine

- Coolant heater
- Oversize batteries
- Extra fuel pre filter water separator

• Alternator

- 12 wire reconnectable stator / Terminal arrangement
- Upgrade to AVR MX321
- Quadrature droop kit
- Anti-condensation heater
- Air inlet filters

• General

- Upgrade to modular controller for paralleling.
- Automatic transfer switch
- Battery charger
- Upgrade to 4 pole ACB
- Fuel tank base frame integrated for 8 hours operation
- Fuel tank separate with customized capacity and shape
- Fuel level switch High / Low for alarm and control
- Fuel transfer pump Automatic / Manual
- Fuel tank air filter
- Residential grade silencer
- Weather protective and acoustic enclosure.



P.O.Box: 235834, Al-Qusais Industrial Area 1,
Plot No 233-0, Warehouse No S.11, Dubai- UAE

Tel: +971 (0) 42636268

Email: info@synergypowertrading.com

Website: www.synergypowertrading.com